MicroLink 56k Fun USB

devolo V.92 modem with USB interface

Technical specifications

Transmission rates	Receive: 300–56000 bps asynchronous Send: 300–33600 bps asynchronous (V.92, V.90, V.34, V.32bis, V.32, V.22bis, V.22, V.21, V.23)
Command set	AT command set according to V.250/V.25ter
Data compression	V.42bis and V.44
Error correction	V.42
Fax operation	2400–14400 bps according to V.17, V.29 and V.27ter; Fax command set class 1 (TIA/EIA-578) and class 1.0 (T.31)
Voice operation	Voice command set: V.253
Dialing method	Multi-frequency dialing
External line access	Via flash function or figure
Bit-rate adaption	Automatic, according to V.8
Computer interface	USB
Power supply	Via USB—no external power adapter required
Weight	140 g
Electric power consumption	Transmission phase (online): 92 mA typ.; command phase (offline): 23 mA typ.
Environment	5–40°C (= 41-104°F), 0–80% humidity (non-condensing)
System requirements	▪ Free USB interface to connect the modem to the PC ▪ CD-ROM drive for software installation ▪ Analog connection
Operating systems	Windows® 98, Windows® 2000, Windows® Me, Windows® XP, Windows® Vista$_{32bit}$
Approvals	CE compliant in accordance with all technical requirements for all EU countries and Switzerland

Sales information

Article numbers	01047 (DE) 01048 (AT) 01049 (CH)
EAN code	4250059610477 (DE) 4250059610484 (AT) 4250059610491 (CH)
Warranty	3 years
Service and Support line	Phone: 0180-5338656 (within Germany) E-mail: support@devolo.de
On-Site Help	Phone: 01805-665066 (within Germany)
Sales	Phone: +49 (0)241-1827979 Fax: +49 (0)241-1827997 E-mail: vertriebsinfo@devolo.de
Design	Plastic housing
Weight	510 g
Packaging size	188 x 234 x 71 mm (height x width x depth)
Accessories	▪ USB connection cable ▪ Telephone connection cable ▪ Documentation: Windows® drivers (98, Me, 2000, XP), PDF manual, NORMAN Internet Control

devolo AG
Sonnenweg 11
52070 Aachen
Germany

Tel.: +49 (0) 241 18279 79
Fax: +49 (0) 241 18279 99
E-mail: info@devolo.com
Internet: www.devolo.com

Status: 17.08.07